

## Idinio Zigbee 2-wire Built-in Dimmer




Upgrade your old fashioned luminaire with Zigbee functionalities. Compatible with most Zigbee powered systems like Philips Hue and Homey- Touchlink support for easy pairing to e.g. Zigbee remotes. Upgrade your existing 'stupid' luminaire with the Idinio Zigbee 2. Wire Built-in Dimmer and add it to most of the popular Zigbee powered lighting systems thanks to the integrated Zigbee 3.0 protocol. Easily turn on/off/dim your luminaire by using the physical knob or the app of the respective lighting brand.

**Article number** 140300

**EAN** 8720246200218

**Brand**



### Smart switching and dimming

Compatible with	2-wire systems
Neutral required	No
Fits to European frames and switch paddles	Yes
Fits to European flush cans	Yes
Min. depth of built-in installation box	26.20 mm
Memory function (colour / dim)	Yes
Max. load INC/HAL	300 W
Max. load LED	200 VA

### Smart home

Smart home category	Smart dimming and switching
Smart home platform	Athom Homey, Philips Hue
Smart home protocol	ZigBee
Area of application	Indoor
On/off switch	Yes
Reset button	Yes
Network connection type	Wireless

### Electrical parameters

Standby power	0.70 W
---------------	--------

### Performance parameters

IP rating	IP20
Operating temperature	0   40 °C

### Mechanical parameters

Dimension of article length	70 mm
Dimension of article height	45 mm
Dimension of article width	70 mm
Net weight of article	0.05 kg
Color housing	Red

Networked standby power	0.50 W
Input voltage	220   240 V
Input frequency	50 Hz
Input current	1.30 A
Power factor	0.90
Safety class	II
Dimming methods	Trailing-edge